

```
#!/bin/bash
clear
cd /sys/class/gpio
if [ -d "gpio20" ]; then
    echo "gpio20 existe déjà"
else
    echo "gpio20 : Création"
    echo 20 > export
fi
cd gpio20/
echo out > direction
echo 0 > value
x="1"
while [ $x -gt 0 ]
do
    echo 1 > value
    echo "LED allumée"
    sleep 1
    echo 0 > value
    echo "LED éteinte"
    sleep 1
done
```